

# RCL03 Mini receiver

## 12-24 V AC / 12-32 V DC 2-channel



The RCL03 mini receiver is primarily used to expand existing systems.

With its two potential-free relay contacts, a wide variety of systems can be expanded with a wireless interface. Converting a garage door opener is just as easy as integrating Easywave transmitters into house call systems.

The RCL03 is powered by 12-24 V AC or 12-32 V DC and can be programmed with up to 32 transmission codes.

The compact housing can be screwed shut if necessary and offers protection against dust and water.



RCL03E5002B10

### Technical specifications

Coding	Easywave Up to 32 transmitters can be programmed.
Frequency	868.30 MHz
Channels	2
Power supply	12-24 V AC / 12-32 V DC
Power consumption	0,18 W standby 0,6 W max. without load
Operating modes	DEAD MAN ON/OFF (2-button operation) PULSE (1 second) ROLLER BLIND MOTOR CONTROL (2-button operation) ROLLER BLIND MOTOR CONTROL (3-button operation)
Inputs	2 external buttons
Outputs	2 potential-free relay contacts (changeover)
Maximum contact load	
- AC	120 V / 1 A / 62 VA
- DC	50 V / 1 A / 30 W
Operating temperature	-20 °C to +60 °C
Protection degree	IP54 (housing screwed, cable correctly mounted)
Dimensions (W/L/H)	80,4/65,5/29,5 mm
Color	white similar RAL 9003

### Scope of delivery

- Mini receiver
- Adhesive pad
- Mounting material
- Housing screws
- Operating manual

### Models

Product number	Description
RCL03E5002B10	Mini receiver, Easywave, 12-24 V AC / 12-32 V DC, 2x changeover, potential-free, white

### Wiring diagram

